

Optimal electron entangler and single electron source at low temperatures

Y. Sherkunov, Jin Zhang, N. d'Ambrumenil, and B. Muzykantskii
Department of Physics, University of Warwick, Coventry, CV4 7AL, UK

Electron transport in mesoscopic contacts at low temperatures is accompanied by logarithmically divergent equilibrium noise. We show that this equilibrium noise can be dramatically suppressed in the case of a tunnel junction with modulated (time-dependent) transparency, and identify the optimal protocol. We show how such a contact could be used either as an optimal electron entangler or as a single-electron source with suppressed equilibrium noise at low temperatures.

The controlled production, manipulation and detection of entangled particles are central to quantum computation. Considerable progress has been made on the manipulation of several qubits in quantum optics [1]. Given the controllability of device parameters and the rapid and coherent transport through mesoscopic contacts, one expects that electrons could also be used to process quantum information [2]. Although the entanglement of electron quasiparticles has not been demonstrated experimentally, important steps towards the detection of entangled states in mesoscopic systems have been taken [3] and there are many theoretical proposals on how to generate, manipulate and detect the entangled electrons in mesoscopic systems [2, 4, 5, 6, 7, 8, 9, 10].

Another breakthrough in ‘electronic optics’ is the experimental demonstration of a single-electron source on demand with sub-nanosecond time resolution [11]. Fève *et.al.* used the coupling of the localized level of a quantum dot to a ballistic conductor to obtain a sequence of single-electron pulses [11].

To manipulate entangled electrons in mesoscopic systems requires low electron temperatures, T [12]. However, when $Tt_f \ll 1$ (t_f is the measurement time), the problem of equilibrium noise associated with the opening and closing of channels arises [13]. If the connection-disconnection process is abrupt, this leads to a logarithmically divergent (so-called) equilibrium noise $\langle\langle Q^2 \rangle\rangle \propto \log t_f/\tau_s$, where τ_s is the characteristic switching time [13] (see also [14]).

Here, we show how the appropriate choice of the time-dependence of the barrier transparency in a tunnel junction can dramatically reduce the equilibrium noise. We suggest how such point contacts could be used as sources for entangled quasiparticles and ultracold single electrons. Firstly, we describe a source of entangled particles, based on two one-dimensional wires coupled by a tunnel junction with tunable transmission and reflection amplitudes A and B , which attains the theoretical maximum entanglement of 50% [7]. We show that tuning the transparency amplitude to take the time-dependent form $A = \text{Im} \prod_j^N \frac{t-t_j-i\tau_j}{t-t_j+i\tau_j}$ ($\tau_j > 0$, or $\tau_j < 0 \forall j$) leads to the excitation of N independent spin-entangled particle-hole pairs, with finite τ_j -independent noise. In the special case $N = 1$, the particle and hole are distributed independently between two leads with probability $1/2$ to find the

particle (or the hole) in either lead. Our proposed scheme is similar to the one based on the quantum pump [7] but with no logarithmically divergent equilibrium noise.

Secondly, we propose a single-electron source, based on a biased quantum point contact with tunable transparency. It has been shown [15, 16], that a Lorentzian voltage pulse $V(t)$ applied between the leads of a quantum point contact excites a single electron (or hole), provided the Faraday flux, $\psi = e/\hbar \int^t V(t')dt'$, is an integer multiple of 2π . Even at low temperatures the transport of a single electron is again accompanied by the logarithmically divergent equilibrium noise, which makes detection of the excitation difficult. We show that the equilibrium noise in the scheme proposed in [15] can be suppressed by tuning the barrier transparency to be $A = \text{Im} \frac{(t+t_1/2-i\tau_1)(t-t_1/2+i\tau_1)}{(t+t_1/2+i\tau_1)(t-t_1/2-i\tau_1)}$. If a quantized Lorentzian pulse is applied between the leads when the barrier is open, the tunnel junction will operate as a very low noise single-electron source.

The noise in the charge transferred across a point contact and the degree of entanglement of states on either side of the contact can be controlled by the time-dependence of the barrier transparency. The noise in the charge transferred across the barrier will be given by $\langle\langle Q^2 \rangle\rangle = \int dt dt' [2A(t)^2 A(t')^2 n_L(1-n_R) + A(t)B(t)A(t')B(t')(n_L(1-n_R) + (1-n_L)n_R)]$, where $A(t)$ and $B(t)$ are the (time-dependent) transmission and reflection amplitudes of the barrier, $n_{L(R)}$ is the density matrix of incoming states in the left (right) lead [17]. With no bias voltage, $n_{L,R} = n_0 = i/[2\pi(t-t' + i0)]$. If the transparency amplitude A switches abruptly, $A \neq 0$ for $t \in [0, t_f]$ and $A = 0$ otherwise, one obtains the well-known logarithmically divergent result for the zero bias ($V = 0$) noise $\langle\langle Q^2 \rangle\rangle_0 = \frac{A^2}{\pi^2} \log t_f/\tau_s$. This logarithmic divergence is an unavoidable consequence of the abrupt start and finish to the measurement and simply reflects the density fluctuations of fermions in 1D crossing any point during a time-interval $[0, t_f]$. If, instead, we choose $A = \text{Im} \frac{t-i\tau}{t+i\tau}$, we obtain $\langle\langle Q^2 \rangle\rangle_0 = 1/2$. As we show below, this result could be used together with the spin degree of freedom of electrons to define an optimum entanglement protocol.

By combining a smooth opening of the contact and the application of a voltage bias between the leads, we show that it is possible to operate the contact as

a single electron source with high signal-to-noise ratio. We propose tuning the barrier height so that $A(t) = \text{Im} \frac{(t+t_1/2-i\tau_1)(t-t_1/2+i\tau_1)}{(t+t_1/2+i\tau_1)(t-t_1/2-i\tau_1)}$, with $\tau_1 = t_1(1/2 + 1/\sqrt{2})$, which ensures that the transparency amplitude goes through a single maximum at $t = 0$ with $A(0) = 1$. If a quantized bias voltage pulse is applied between the leads, $n_L = n_0$, $n_R = e^{i\psi} n_0 e^{-i\psi}$ with $e^{i\psi} = \frac{t-t_0-i\tau_0}{t-t_0+i\tau_0}$, which is narrow in time ($\tau_0 \ll \tau_1$), we should expect $\langle\langle Q^2 \rangle\rangle \approx \langle\langle Q^2 \rangle\rangle_0 + |A(t_0)|^2(1 - |A(t_0)|^2)$. The first term describes the zero bias noise associated with the opening of the contact and the second gives the shot noise for an open contact [13]. For $t_0 = 0$ the second term can be made to vanish so that for this choice of τ_1/t_1 , we should expect that $\langle\langle Q^2 \rangle\rangle \approx \langle\langle Q^2 \rangle\rangle_0 \approx 1/4$.

The statistics of the transferred charge are encoded in the characteristic function, $\chi(\lambda)$ [18]:

$$\chi(\lambda) = \sum_{n=-\infty}^{+\infty} P_n e^{in\lambda}. \quad (1)$$

Here P_n is the probability of n particles being transmitted across a barrier. A variety of approaches have been used to study $\chi(\lambda)$, with the majority focused on voltage-biased contacts [15, 18, 19, 20, 21, 22, 23]. We find a mapping between the problem of the biased leads and that of the time-dependent barrier transmission. Our formulation of the problem enables us to solve for $\chi(\lambda)$ analytically in an unbiased contact and to compute numerically the characteristic function for a time-dependent transmission amplitude in the presence of bias voltages.

The system we consider is a 2-terminal mesoscopic contact at zero temperature, which consists of two single-channel leads and a barrier characterised by transmission and reflection amplitudes, A and B . The annihilation operators of the incoming states $a_{L(R)}$ are related to the outgoing states $b_{L(R)}$ at the left (right) lead via:

$$\begin{pmatrix} b_L \\ b_R \end{pmatrix} = S \begin{pmatrix} a_L \\ a_R \end{pmatrix} \quad \text{with} \quad S = \begin{pmatrix} B & A \\ -A^* & B^* \end{pmatrix}, \quad (2)$$

where the scattering matrix S varies slowly compared to the Wigner delay time. We will take A and B to be real. Then, in the (time-independent) basis in which the scattering matrix is diagonal, the incoming states $\tilde{a}_1 = \frac{1}{\sqrt{2}}(a_L - ia_R)$ and $\tilde{a}_2 = \frac{1}{\sqrt{2}}(a_L + ia_R)$. In this basis $S_{11} = e^{i\phi(t)}$, $S_{22} = e^{-i\phi(t)}$, $S_{12} = S_{21} = 0$, where $e^{i\phi(t)} = B(t) + iA(t)$, and the outgoing states are $b_L = \frac{1}{\sqrt{2}}(\tilde{a}_1 e^{i\phi} + \tilde{a}_2 e^{-i\phi})$ and $b_R = \frac{i}{\sqrt{2}}(\tilde{a}_1 e^{i\phi} - \tilde{a}_2 e^{-i\phi})$.

The relation between the channels 1 and 2 and those of the two leads L and R is the electronic equivalent of a beam splitter. This is illustrated in Fig.1a for the case of single excitations in channels 1 and 2. The time-dependence of the barrier excites a particle-hole pair in channel 1 with probability $\sin^2 \frac{\alpha_1}{2}$ and another in channel 2 with probability $\sin^2 \frac{\alpha_2}{2}$. For the unbiased case, reflection and transmission of particles in channels 1 and 2




Figure 1: (color online) Charge transport through an unbiased contact with time-dependent scattering matrix. (a) Particle-hole excitations induced in channels 1 and 2 (in which the scattering matrix is diagonal) can be thought of as propagating through a 50% beam-splitter to yield the charge in the left (L) and right leads (R) of the contact. (b) Outcomes of applying the pulse (6) to the barrier of the tunnel junction. A hole (white) and an electron (black) occupies states in both leads with probability $1/2$.

occur independently. The probability of finding no additional charge in the right lead as a result of the excitation in channel j is then $P_0 = \cos^2 \frac{\alpha_j}{2} + \frac{1}{2} \sin^2 \frac{\alpha_j}{2}$, while the probability of finding an additional particle or hole are: $P_{\pm 1} = \frac{1}{4} \sin^2 \frac{\alpha_j}{2}$. The characteristic function $\chi(\lambda)$ is the product of the results from the two independent channels:

$$\chi(\lambda) = \prod_j \left(1 + \frac{1}{4} \sin^2 \frac{\alpha_j}{2} (e^{i\lambda} + e^{-i\lambda} - 2) \right). \quad (3)$$

The angles α_j can be found by diagonalizing the matrix $h_1 h_2$ [21, 23]:

$$h_1 h_2 = e^{i\phi} h e^{-i\phi} e^{-i\phi} h e^{i\phi}, \quad (4)$$

where $h = 2n_0 - 1$ is related to the density matrix, n_0 , of the ground state. The eigenvalues of $h_1 h_2$ are paired and equal to $e^{i\alpha}, e^{-i\alpha}$ [21, 23]. In the case of a voltage-biased contact, there can also be unpaired eigenvalues, corresponding to so-called unidirectional events, in which a single particle or hole is excited.

Eq.(3) formally coincides with the one obtained for $\chi(\lambda)$ for bidirectional events in a quantum contact. For a (zero-mean) time-dependent bias, $V(t)$, between the leads and a barrier which is described by a time-independent scattering matrix [21]: $\chi(\lambda) = \prod_j (1 + |A|^2 |B|^2 \sin^2 \frac{\alpha_j}{2} (e^{i\lambda} + e^{-i\lambda} - 2))$. Setting $|A|^2 = |B|^2 = \frac{1}{2}$, gives the result (3). In the case of the biased contact the angles α_j are found by diagonalizing $e^{i\psi(t)} h e^{-i\psi(t)} h$, where $\psi = e/\hbar \int^t V(t') dt'$ is the Faraday flux. Direct comparison with Eq.(4) shows that the problem of the unbiased quantum contact with time-dependent scatterer is equivalent to the problem of a voltage biased quantum contact with time-independent scatterer if: $\psi \rightarrow 2\phi$, $|A|^2 \rightarrow 1/2$, $|B|^2 \rightarrow 1/2$.

As an illustration of the power of this mapping, we consider the case of a periodically modulated transparency

$A = \sin(\omega t)$, $B = \cos(\omega t)$. The mapping means that this problem is equivalent to that of a contact under constant bias. The characteristic function for this case is known to be $\chi(\lambda) = [\chi_0(\lambda)]^{\frac{t_f \omega}{2\pi}}$ [18], where χ_0 describes a single period, and t_f is the measurement time. The eigenvalues of the matrix $he^{2i\omega t}he^{-2i\omega t'}$ for a single period are paired and equal to -1 . Using this to compute $\chi(\lambda)$ for a barrier with periodically modulated transparency gives: $\chi(\lambda) = [(1 + \cos \lambda)/2]^{\omega t_f/2\pi}$ which is a result previously obtained by Andreev and Kamenev [24].

The problem of voltage-biased quantum point contacts with constant transparency amplitude A , where a voltage $V(t)$ is applied to one of the leads of a tunnel junction has been extensively studied [13, 15, 18, 21, 23]. Particular attention has been paid to the case of quantized Lorentzian voltage pulses applied to one electrode $V(t) = \sum_j^N \frac{-2\tau_j}{(t-t_j)^2 + \tau_j^2}$ ($\tau_j > 0$ or $\tau_j < 0 \forall j$) when

$$e^{i\psi(t)} = \prod_{j=1}^N \frac{t - t_j - i\tau_j}{t - t_j + i\tau_j}. \quad (5)$$

If $\tau_j > 0$ or $\tau_j < 0$ the pulse excites exactly N particles or holes depending on the polarity of the device [15, 16].

Some of the results obtained for the problem of the biased point-contact, when mapped to the time-dependent barrier case, help with the design of an optimum entangler of particle states and the design of low noise sources of cold electrons and holes. From (5), we can see the special status of events in which the barrier is modulated according to

$$e^{i\phi} = B + iA = \sqrt{\left(\frac{t - i\tau}{t + i\tau}\right) \left(\frac{t - t_1 - i\tau}{t - t_1 + i\tau}\right)}. \quad (6)$$

(In the case $t_1 = 0$, Eq.(6) describes a single pulse of the type (5).) The characteristic function, $\chi(\lambda)$, is found from the eigenvalues of $h_1 h_2$ (see Eq.(4)), which are the same as those of $he^{2i\phi}he^{-2i\phi}$. In the language of the biased lead case, these are just two so-called uni-directional events and both eigenvalues are equal to -1 , so $\alpha_{1,2} = \pi$ [23]. From (3) we then obtain $\chi(\lambda) = \frac{(1 + \cos \lambda)}{2}$. The four possible outcomes of applying the pulse (6) to the barrier are illustrated in Fig.1b and all occur with probability $1/4$.

The particle and the hole in Fig.1b are entangled. However, this entanglement cannot be revealed by measurements because of particle number conservation [5]. In order to create “useful” entangled states, which can be measured with the Bell procedure, we should consider entanglement in, for example, the spin degree of freedom of the particles. Taking account of spin, each lead has two channels: one for each spin projection. If we suppose that the scattering matrix for the barrier is spin-independent (so that the two channels in each lead are independent), and a pulse (6) is applied, we have $\chi(\lambda) = [\frac{1}{2}(1 + \cos \lambda)]^2$.

There are now 16 outcomes which occur with equal probabilities. The fully entangled Bell pair is created only if the change in charge in one of the leads is $+1$ and -1 in the other, and occurs with probability $1/2$. The measurement procedure requires measurement of the charge in one of the leads first, and then of the spin state of the particle or hole.

To calculate the available entanglement entropy, one should use the super-selection rules, which account for particle number conservation [25] (see also [26, 27]). Let a quantum state, with N particles distributed between Alice and Bob (left and right leads), be described by a wavefunction $|\Psi_{AB}\rangle$ and let $|\Psi_{AB}^n\rangle$ be the wavefunction projected onto a subspace of fixed local particle number n for Alice and $N - n$ for Bob. The available entropy is: $S_{avl} = -\sum_n P_n \ln P_n$, where P_n is the probability $P_n = \langle \Psi_{AB}^n | \Psi_{AB}^n \rangle / \langle \Psi_{AB} | \Psi_{AB} \rangle$ and S_n is the standard entanglement entropy corresponding to the configuration n . The probability to find a particle in the left lead and a hole in the right lead or vice versa is $1/4$. The entanglement entropy of the configurations containing a fully entangled Bell pair is $S_n = 1$. Thus we find $S_{avl} = 1/2$. This corresponds to an entangler with 50% efficiency, which is the optimal value. The entangler proposed originally in [7] has the same efficiency but still contains the equilibrium noise, which in our proposal is suppressed. Finally we note that for the case of N pulses

applied to the barrier $e^{i\phi} = \prod_j^N \sqrt{\left(\frac{t - t_j - i\tau_j}{t - t_j + i\tau_j}\right) \left(\frac{t - t'_j - i\tau_j}{t - t'_j + i\tau_j}\right)}$ ($\tau_j > 0$ or $\tau_j < 0 \forall j$) we find $\chi(\lambda) = \left(\frac{1 + \cos \lambda}{2}\right)^N$, i.e. the particle-hole pairs are produced independently.

Now we turn our attention to the ultracold single-electron source. We consider a tunnel junction with tunable transparency, which connects two single-channel wires. A single quantized voltage pulse, with $e^{i\psi} = \frac{t - t_0 - i\tau_0}{t - t_0 + i\tau_0}$, is applied to one of the leads, and a single particle is excited [15]. If the barrier transparency is turned on abruptly, the logarithmically divergent equilibrium noise emerges and makes measurement of a single unidirectional event problematic. To suppress the equilibrium noise, we propose modulating the barrier smoothly, by applying a pulse sequence to the barrier with:

$$e^{i\phi} = B + iA = \left(\frac{t + t_1/2 - i\tau_1}{t + t_1/2 + i\tau_1}\right) \left(\frac{t - t_1/2 + i\tau_1}{t - t_1/2 - i\tau_1}\right). \quad (7)$$

We choose $\tau_1 = t_1(\frac{1}{2} + \frac{1}{\sqrt{2}})$. This choice gives a transparency amplitude, which does not change sign and goes through a single maximum at $t = 0$, with $|A(0)|^2 = 1$, as shown in Fig.2a.

The characteristic function in the general case of quantum pumping can be expressed in terms of the eigenvalues of the single-particle density matrix of outgoing states in, say, the left lead $n_{out} = \langle b_L^\dagger b_L \rangle = B^* n_0 B + A^* \tilde{n} A$. Here $\tilde{n} = e^{i\psi} n_0 e^{-i\psi}$. Consider first the case of a single-particle excitation in the outgoing states. The eigenval-




Figure 2: (color online) Single unidirectional event in a quantum contact with tunable transparency. (a) Transparency of the barrier, $|A(t)|^2$, as a function of time (see 7). Also shown is the quantized voltage pulse, $V(t)$, applied to the left lead; (b) Average charge transfer through the barrier, $\langle Q \rangle$, as a function of t_0/τ_1 , where t_0 is the separation between the maxima of $V(t)$ and $|A(t)|^2$, see Fig. 2(a). The maximum of $\langle Q \rangle$ occurs when $t_0 = 0$ where $|A|^2$ approaches 1, it grows as the width of the voltage pulse, τ_0 , is reduced, and is close to 1 for $\tau_0 = \tau_1/16$. (c) Noise, $\langle\langle Q^2 \rangle\rangle$, in a biased contact with transparency given by (7) as a function of t_0/τ_1 . The minimum of $\langle\langle Q^2 \rangle\rangle$ occurs for $t_0 = 0$ and, for a narrow voltage pulse ($\tau_0 = \tau_1/16$), it approaches the limit set by the barrier modulation: $\langle\langle Q^2 \rangle\rangle_0$ (horizontal dashed line). The maxima in the noise occur when $t_0/\tau_1 \approx 1$ and $|A|^2 \approx 1/2$.

ues of the density matrix in the left lead are 1 (for the states below the Fermi level), 0 (for the states above the Fermi level not occupied by the excitation) and n_j for the state affected by the excitation. The characteristic function (1) is then $\chi_p(\lambda) = 1 - n_j + e^{i\lambda}n_j$. For a single hole in the outgoing states we find $\chi_h(\lambda) = n_j + e^{-i\lambda}(1 - n_j)$. These two formulae can be combined to give $\chi(\lambda) = e^{i(Q_1 - n_j)\lambda}(1 - n_j + e^{i\lambda}n_j)$. (The transferred charge $Q_1 = n_j$ for the particle excitation and $Q_1 = n_j - 1$ for the hole excitation.) In the general case the density matrix is Hermitian and thus possesses an orthonormal eigenbasis, and we arrive at the formula of [28]: $\chi(\lambda) = e^{i\lambda Q} \prod_j e^{-i\lambda n_j} [1 + (e^{i\lambda} - 1)n_j]$ where Q is the total transferred charge.

For the case of the pulse (7) applied to the barrier together with the bias pulse $e^{i\psi} = \frac{t-t_0-i\tau_0}{t-t_0+i\tau_0}$ applied to the left lead, we have diagonalized the density matrix n_{out} numerically. In Fig.2c we present results for the noise $\langle\langle Q^2 \rangle\rangle$ in the system as a function of the separation t_0 between the bias pulse and the barrier pulses. The maximum values of the noise occurs when $t_0 \approx \tau_1$ and the transparency coefficient is almost $1/2$. This is the regime where the barrier is acting as a 50% beam-splitter. The minimum of $\langle\langle Q^2 \rangle\rangle$ corresponds to $t_0 = 0$, when $|A|^2 = 1$. At $t_0 = 0$ the transferred charge also reaches its maximum (see Fig.2b). If the bias pulse is narrow compared to the barrier pulse ($\tau_0 \ll \tau_1$), the major contribution to the noise at the minimum is very close to the value

expected on the basis of our earlier heuristic argument, namely $\langle\langle Q^2 \rangle\rangle_0$ and the transferred charge approaches 1. This is the regime which we are proposing could be used as a single-electron source on demand at ultralow temperatures.

The work was supported by EPSRC-EP/D065135/1.

-
- [1] P. Kok, W. J. Munro, K. Nemoto, T. C. Ralph, J. P. Dowling, and G. J. Milburn, *Rev. Mod. Phys.* **79**, 135 (2007).
 - [2] C. W. J. Beenakker, in *Proc. Int. School Phys. E. Fermi* (IOS Press, Amsterdam, 2006).
 - [3] I. Neder, N. Ofek, Y. Chung, M. Heiblum, D. Mahalu, and V. Umansky, *Nature* **448**, 333 (2007).
 - [4] P. Samuelsson and M. Büttiker, *Phys. Rev. B* **71**, 245317 (2005).
 - [5] C. W. J. Beenakker, D. P. DiVincenzo, C. Emary, and M. Kindermann, *Phys. Rev. Lett.* **93**, 020501 (2004).
 - [6] B. Trauzettel, A. N. Jordan, C. W. J. Beenakker, and M. Büttiker, *Phys. Rev. B* **73**, 235331 (2006).
 - [7] C. W. J. Beenakker, M. Titov, and B. Trauzettel, *Phys. Rev. Lett.* **94**, 186804 (2005).
 - [8] A. V. Lebedev, G. Blatter, C. W. J. Beenakker, and G. B. Lesovik, *Phys. Rev. B* **69**, 235312 (2004).
 - [9] P. Samuelsson, E. V. Sukhorukov, and M. Büttiker, *Phys. Rev. Lett.* **92**, 026805 (2004).
 - [10] A. D. Lorenzo and Y. V. Nazarov, *Phys. Rev. Lett.* **94**, 210601 (2005).
 - [11] G. Fève, A. Mahé, J.-M. Berroir, T. Kontos, B. Placais, D. Glatelli, A. Cavanna, B. Etienne, and Y. Jin, *Science* **316**, 1169 (2007).
 - [12] P. Samuelsson, I. Neder, and M. Büttiker, *cond-mat/0808.4090* (2008).
 - [13] L. Levitov, H. Lee, and G. Lesovik, *J. Math. Phys.* **37**, 4845 (1996), *cond-mat/9607137*.
 - [14] M. Moskalets and M. Büttiker, *Phys. Rev. B* **75**, 035315 (2007).
 - [15] D. A. Ivanov, H. W. Lee, and L. S. Levitov, *Phys. Rev. B* **56**, 6839 (1997).
 - [16] J. Keeling, I. Klich, and L. S. Levitov, *Phys. Rev. Lett.* **97**, 116403 (2006).
 - [17] H. Lee and L. Levitov (1993), *cond-mat/9312013*.
 - [18] L. Levitov and G. Lesovik, *JETP Letters* **58**, 230 (1993).
 - [19] B. Muzykantskii and Y. Adamov, *Phys. Rev. B* **68**, 155304 (2003).
 - [20] N. d'Ambrumenil and B. Muzykantskii, *Phys. Rev. B* **71**, 045326 (2005).
 - [21] M. Vanević, Y. V. Nazarov, and W. Belzig, *Phys. Rev. Lett.* **99**, 076601 (2007).
 - [22] M. Vanević, Y. V. Nazarov, and W. Belzig, *Phys. Rev. B* **78**, 245308 (2008).
 - [23] Y. B. Sherkunov, A. Pratap, B. Muzykantskii, and N. d'Ambrumenil, *Phys. Rev. Lett.* **100**, 196601 (2008).
 - [24] A. Andreev and A. Kamenev, *Phys. Rev. Lett.* **85**, 1294 (2000).
 - [25] H. M. Wiseman and J. A. Vaccaro, *Phys. Rev. Lett.* **91**, 097902 (2003).
 - [26] I. Klich and L. Levitov, *quant-ph/0804.1377* (2008).
 - [27] I. Klich and L. Levitov, *quant-ph/0812.0006* (2008).
 - [28] A. G. Abanov and D. A. Ivanov, *Phys. Rev. Lett.* **100**,

086602 (2008).